



The world's leading supplier of broadband power amplifiers.

Model #: 7T1000M-8C Frequency Range: 40-305 MHz

### Specifications\*



Operating frequency	40-305 MHz
Pulse power into 50 ohms per channel	1000 W (min.)
CW power	50 W
Pulse width	20-100 msec typical.
Linearity (+/-1 dB, class AB )	1000 W (min.)
Gain (0 dBm input)	+ 60 dB (nominal)
Gain flatness	+/- 3 dB, typ.
Harmonic content (2nd/3rd)	-20 dB/ -12 dBc, typ.
Input/ Output impedance	50 ohms (nominal)
Input VSWR	Less than 2:1
Duty cycle	10% (max.)
Amplitude rise/fall time	250 ns, typ.
Amplitude droop	5% to 20 ms. typ., 8% max.
Phase change / output power	12° to rated power, typ. 25° max.
Phase error overpulse	5° to 10 ms duration, typ.
Noise figure	12 dB typ.
Output noise (blanked)	20 dB over thermal, typ.
Blanking delay	1 μs, typ., on/off, TTL signal

#### Communication Power Corporation

80 Davids Drive, Suite 3  
Hauppauge, New York 11788  
Phone: 631. 434. 7306 Fax: 631. 434. 7026  
email: info@cpcamps.com  
Web Site: www.CPCAMPS.COM

\* CPC reserves the right to change specifications without notice.



The world's leading supplier of broadband power amplifiers.

Model #: 7T1000M-8C Frequency Range: 40-305 MHz

## System Features

Printer  
Friendly  
Version



### Protection functions:

- Auto/manual fault reset
- Maximum forward power
- Maximum average power
- Maximum VSWR
- Over temperature
- Power supply over voltage

### Controls, front panel:

- AC power on/off
- Forward/ Reflected RF Power
- Fault reset
- Low power mode

### Connectors, rear panel:

- AC mains, Receptacles, EMI filtered
- RF input: BNC (F) X8
- RF output: Type N (F) X8
- Noise blanking: BNC (F) dual polarity X8
- Interface: 25 pin D (F), EMI filtered
- Fwd/ Ref RF sample: SMA (F) X8
- Protective ground: threaded bolt

### Front panel indicators:

- |                    |                     |
|--------------------|---------------------|
| AC power on        | CW mode             |
| Standby mode       | Power supply status |
| RF overdrive fault | Thermal fault       |
| VSWR fault         | Blanking (Gate)     |
| Energy fault       |                     |

### Interface functions:

- (C= Control Input F= Flag Output)
- CW mode (C/F)      Standby (C/F)
- Power supply (F)      RF overdrive (F)
- Thermal (F)      VSWR (F)
- Energy (F)

\* CPC reserves the right to change specifications without notice.

**Communication Power Corporation**  
80 Davids Drive, Suite 3  
Hauppauge, New York 11788  
Phone: 631. 434. 7306 Fax: 631. 434. 7026  
email: info@cpccamps.com  
Web Site: www.CPCAMPS.COM



The world's leading supplier of broadband power amplifiers.

Model #: 7T1000M-8C Frequency Range: 40-305 MHz



### Environmental



Printer  
Friendly  
Version

Cooling Internal forced air, front to back flow

Operating temperature +10 to 40°C

AC line voltage 208 VAC, +/-10%, 47-63 Hz

Chassis size 78 x 27 x 40 (HWD, inches)

Net weight 1200 lbs. (approx.)

Compliance CE, UL 2601 upon request

#### Communication Power Corporation

80 Davids Drive, Suite 3  
Hauppauge, New York 11788  
Phone: 631.434.7306 Fax: 631.434.7026  
email: [info@cpcamps.com](mailto:info@cpcamps.com)  
Web Site: [www.CPCAMPS.COM](http://www.CPCAMPS.COM)

\* CPC reserves the right to change specifications without notice.